



Mini 100

User Manual



EN Welcome to VAPEBERRI and thank you for purchasing our product. You must be 18 years or older to purchase or use this product.

Specification :

Variable wattage: 5.0w-100.0w

Kanthal A1 Coil Res: 0.2 Ω -3.0 Ω

Ni200 Coil Res : 0.2 Ω -1.0 Ω

Ti1 Coil Res : 0.18 Ω -1.0 Ω

SS316 Coil Res : 0.2 Ω -1.0 Ω

Temp Control : 200°F - 600°F and 100°C - 300°C

Size: 75*41*28mm

Battery : 2300mah 30A 20600 Battery

Connection: Stainless Steel Spring Loaded 510 Connection

Main Features:

Visual Operating System

Low Voltage Protection



Low Resistance Protection

Output Short Circuit Protection

Reverse Battery Protection

Temperature Overheat Protection

Temp Control (100°C-300°C/200°F-600°F)



How to Use:

1. Five click the Fire button to turn ON the device. OLED screen show "HELLO". Then displaying: Battery condition, Resistance X.XX Ω , Wattage XX.XW and Coil Type(Ni/Ti/S) temperature XXXF($^{\circ}\text{C}$) or voltage X.XV(Power Mode) .

Five click the Fire button to turn OFF the device.

2. Adjust the Wattage/Temperature: Press the +/- button to increase or decrease the wattage/Temperature by 0.1w/ 1°C / $^{\circ}\text{F}$ each time. The wattage is adjustable vary from 5.0W to 100.0W. And the temperature is adjustable vary from 100°C to 300°C or 200°F to 600°F .

Without any operation in 2 seconds, the screen light will be weak. Without any operation in 15 seconds, the screen will be closed and then go into sleep state, press the Fire button or Mode button

will back to normal state.

3. Menu setting: 3 click the fire button quickly, go into the menu:

MENU		FUNCTION
TC MODE	NI200/TI1/ SS316L	Set the coil type
	CUSTOIN TCR	Set 5 groups Temp coefficient of resistance at 200°F/ 400°F/600°F
POWER MODE		EXIT to wattage adjust
SYSTEM	SCREEN	LEFT/RIGHT/STEALTH
	SENSITIVITY	Adjust the sensitivity to eliquid from 1to 20
	TC COMP	Temperature Compensation from 1 to 99
	COUNT	XXXT(puffs) XXXXS(total time) CLR COUNT(clear count)
EXIT		Back to Normal State

4. In TC MODE, Press the fire button and the + button together, then you can adjust the wattage.

5. Press the fire button and - button at the same time, it will lock the system, when it is locked, you can vape but can't adjust the device. Do the same operation to unlock the system.

6. MODE button function. Press the MODE button, you can change the coil type setting (Ni/Ti/SS) quickly or change to POWER MODE quickly.

7. Press the + and - button together to set the atomizer resistance.

8. In TC MODE, when the atomizer is without e-liquid, the OLED screen will show "NO LIQUID"

How to charge:

Connect USB cable to charge directly.

Precautions:

Only have your Mini 100 repaired by VAPEBERRI. Do not attempt to repair the device yourself as damage or personal injury may occur. Do not leave the Mini 100 in high temperatures or damp conditions because it may be damaged. The appropriate operation temperature is 0°C to 45°C while charging and -10°C to 60°C while using.

Warranty:

Please consult your VAPEBERRI product warranty card. We are not responsible for any damages caused by human error. Our warranty is not available for products purchased from third-party vendors.



Made in China